1N4728UR-1 thru 1N4764UR-1



1W Surface Mount Zener Diode Series

Rev. V1

Features

- Hermetic Glass DO-41 Package
- Double Plug Construction
- Metallurgically Bonded
- Available in JAN JANTXV Equivalents





Electrical Specifications: $T_A = +25^{\circ}C$ (unless otherwise specified)

TYPE NUMBER (Note 1)	NOMINAL ZENER VOLTAGE Vz	ZENER TEST CURRENT I _{ZT}	. Z _{ZT} @ I _{ZT} REVERSE CUR		IMUM LEAKAGE RENT ⊉ V _R	MAXIMUM DC ZENER CURRENT I _{ZM}
	VOLTS	mA	Ω	μΑ	VOLTS	mA
1N4728UR-1	3.3	76	10	100	1.0	276
1N4729UR-1	3.6	69	10	100	1.0	252
1N4730UR-1	3.9	64	9	50	1.0	234
1N4731UR-1	4.3	58	9	10	1.0	217
1N4732UR-1	4.7	53	8	10	1.0	193
1N4733UR-1	5.1	49	7	10	1.0	178
1N4734UR-1	5.6	45	5	10	2.0	162
1N4735UR-1	6.2	41	2	10	3.0	146
1N4736UR-1	6.8	37	3.5	10	4.0	133
1N4737UR-1	7.5	34	4.0	10	5.0	121
1N4738UR-1	8.2	31	4.5	10	6.0	110
1N4739UR-1	9.1	28	5.0	10	7.0	100
1N4740UR-1	10	25	7	10	7.6	91
1N4741UR-1	11	23	8	5	8.4	83
1N4742UR-1	12	21	9	5	9.1	76
1N4743UR-1	13	19	14	5	9.9	69
1N4744UR-1	15	17	16	5	11.4	61
1N4745UR-1	16	15.5	20	5	12.2	57
1N4746UR-1	18	14	22	5	13.7	50
1N4747UR-1	20	12.5	23	5	15.2	45
1N4748UR-1	22	11.5	25	5	16.7	41
1N4749UR-1	24	10.5	35	5	18.2	38

(Continued next page)

VPT Components and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.vptcomponents.com</u> for additional data sheets and product information.

1



1W Surface Mount Zener Diode Series

Rev. V1

Electrical Specifications: $T_A = +25^{\circ}C$ (unless otherwise specified)

TYPE NUMBER (Note 1)	NOMINAL ZENER VOLTAGE Vz	ZENER TEST CURRENT I _{ZT}	Zzī @ Izī C		Kimum E leakage Rrent @ V _R	MAXIMUM DC ZENER CURRENT I _{ZM}
	VOLTS	μA	Ω	μA	VOLTS	mA
1N4750UR-1	27	9.5	35	5	20.6	34
1N4751UR-1	30	8.5	40	5	22.8	30
1N4752UR-1	33	7.5	45	5	25.1	27
1N4753UR-1	36	7	50	5	27.4	25
1N4754UR-1	39	6.5	60	5	29.7	23
1N4755UR-1	43	6	70	5	32.7	22
1N4756UR-1	47	5.5	80	5	35.8	19
1N4757UR-1	51	5	95	5	38.8	18
1N4758UR-1	56	4.5	110	5	42.6	16
1N4759UR-1	62	4	125	5	47.1	14
1N4760UR-1	68	3.7	150	5	51.7	13
1N4761UR-1	75	3.3	175	5	56.0	12
1N4762UR-1	82	3.0	200	5	62.2	11
1N4763UR-1	91	2.8	250	5	69.2	10
1N4764UR-1	100	2.5	350	5	76.0	9

 The JEDEC type numbers shown above have a standard tolerance of +/- 5% of the nominal Zener volume. C suffix signifies 2% tolerance, D suffix signifies 1% tolerance. V_z is measured with the diode in thermal equilibrium at 25°C + 3°C.

 The Zener impedance is derived from the 60Hz ac voltage, which results when an ac current having an rms value equal to 10% of the DC Zener current (I_{ZT} or I_{ZK}) is superimposed on I_{ZT} or I_{ZK}. Zener impedance is measured at two points to insure a sharp knee on the breakdown curve and eliminate unstable units.

 The reverse surge current is measured at 25°C ambient using a 1/2 square wave or equivalent sine wave pulse 1/120 second duration superimposed on I_{ZT}.

Absolute Maximum Ratings

Parameter	Absolute Maximum		
Steady State Power Dissipation	1W @ +25°C		
Forward Voltage	1.2V @ I _F = 200 mA		
R _{oJA}	170 °C/W		
Operating & Storage Temperature	-65°C to +175°C		


VPT Components and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.vptcomponents.com</u> for additional data sheets and product information.

3

1N4728UR-1 thru 1N4764UR-1

1W Surface Mount Zener Diode Series

Outline Drawing (DO-41)



BL


Ltr	Inches		Millim	Notes	
	Min	Max	Min	Max	
BD	.060	.085	1.52	2.16	3
BL	.106	.160	2.69	4.06	3
LD	.028	.032	0.71	0.81	
LL	.800	1.300	20.32	33.02	
LU		.050		1.27	4

NOTES:

- 1. 2.
- Dimensions are in inches. Millimeters are given for general information only. Package contour optional with BD and length BL. Heat slugs, if any, shall be included within this cylinder 3. length but shall not be subject to minimum limit of BD.
- The specified lead diameters apply in the zone between .050 inch (1.27 mm) from the diode body and the 4. end of the lead. 5.

In accordance with ASME Y14.5M, diameters are equivalent to Φx symbology.

FIGURE 1. Physical dimensions of non-surface mount device (DO-41).





LD

Rev. V1

1W Surface Mount Zener Diode Series



VPT COMPONENTS. ALL RIGHTS RESERVED.

Information in this document is provided in connection with VPT Components products. These materials are provided by VPT Components as a service to its customers and may be used for informational purposes only. Except as provided in VPT Components Terms and Conditions of Sale for such products or in any separate agreement related to this document, VPT Components assumes no liability whatsoever. VPT Components assumes no responsibility for errors or omissions in these materials. VPT Components may make changes to specifications and product descriptions at any time, without notice. VPT Components makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF VPT COMPONENTS PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PA-TENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. VPT COMPONENTS FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CON-TAINED WITHIN THESE MATERIALS. VPT COMPONENTS SHALL NOT BE LIABLE FOR ANY SPECIAL, IN-DIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVE-NUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

VPT Components products are not intended for use in medical, lifesaving or life sustaining applications. VPT Components customers using or selling VPT Components products for use in such applications do so at their own risk and agree to fully indemnify VPT Components for any damages resulting from such improper use or sale.

⁴

VPT Components and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice. Visit <u>www.vptcomponents.com</u> for additional data sheets and product information.